

APPARATUS FOR RANDOM ACCESS MEMORY ARRAY SELF-TEST

5

FIELD OF THE INVENTION

The present invention relates generally to random access memories (RAM) in integrated circuits and, more particularly, to the test of such circuits and, even more particularly, to their test on-chip.

10

BACKGROUND OF THE INVENTION

Motivated by the desire for both lower cost and higher performance, integrated circuit (IC) technology has moved throughout its history toward building larger and larger circuits comprising more and more devices. The development of random access memory (RAM) integrated circuits have shared in this movement. In the sense of containing a larger number of memory cells where each cell can store one bit, the larger a RAM becomes, the more difficult and expensive it is to test it. Also, the more expensive the cost of a defect in the circuit, as a single defect can result in the loss of the whole chip.

20

Not only are RAM's fabricated as stand-alone chips, but they are also built embedded as function blocks in other integrated circuits. Such integrated circuits could be designed and produced as standard chips intended for a variety of applications and as application specific integrated circuits (ASIC's).

25

With the size and complexity of modern integrated circuits including RAM's, testing has become an important issue. Size and cost constraints limit the area on the integrated circuit available for use as wire bonding pads, flip-chip solder bumps, and the like with the resultant effect of limiting access to the various functioning areas of the chip. So, not all functions of the chip are externally available for direct test. Even if connections to some of these areas were available, the long traces and additional external

30

circuitry necessary to access them would introduce signal delays that could render the results of such testing questionable. Thus of necessity, some testing circuitry is now often included on-chip.

5 On-chip testing also has its share of difficulties as chip area available for testing is limited, as is accessibility to nodes for testing. Delays introduced by trace lengths also continue to be an issue. In addition unless the chip is designed for mass production, the costs associated with design, manufacturing, and test can be prohibitive.

10 Additional, redundant circuitry is often included in large integrated circuits. Techniques available, as for example laser fusing, permit the removal of defective parts of the IC and its replacement with the redundant part. This process is cost effective, since on average the added cost of the redundant circuitry is less than the cost associated with the yield loss without the additional circuitry. The addition of redundant circuitry is especially valuable for circuits with repeating structure function blocks, such as RAM and other types of memory. In such circuits a limited number of defective cells can be
15 replaced with the redundant cells embedded in the circuitry. Once again, however, unless the chip is designed for mass production, design costs can be prohibitive.

20 Thus since current on-chip techniques for testing RAM function blocks typically require a substantial area on the chip and are typically somewhat removed from the tested area introducing propagation delay errors, there is a need for enhanced means for testing RAM circuits on-chip.

SUMMARY OF THE INVENTION

In one representative embodiment, an electronic circuit for self-test of a random access memory array is disclosed wherein the random access array has a plurality of memory storage cells, wherein the storage cells are organized into a plurality of slice arrays. The electronic circuit includes a control circuit, an address selection circuit, an input/output circuit associated with each slice array, and an error detection circuit. The control circuit directs the address selection circuit to index through memory addresses. The control circuit also directs each input/output circuit to write data into its associated slice array at the indexed memory address, to read data from the associated slice array at the indexed memory address, and to compare the data read from the associated slice array with that written into the associated slice array at the indexed memory address. The error detection circuit collects results of the self-test data comparisons from each input/output circuit and notifies the control circuit of the results of the self-test.

Other aspects and advantages of the present invention will become apparent from the following detailed description, taken in conjunction with the accompanying drawings, illustrating by way of example the principles of the invention.

BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings provide visual representations which will be used to more fully describe the invention and can be used by those skilled in the art to better understand it and its inherent advantages. In these drawings, like reference numerals identify corresponding elements.

Figure 1 is a diagram of the architecture of a RAM circuit as described in various representative embodiments consistent with the teachings of the invention.

Figure 2 is a block diagram of an electronic test circuit as described in various representative embodiments consistent with the teachings of the invention.

Figure 3 is another block diagram of the electronic test circuit as described in various representative embodiments consistent with the teachings of the invention.

Figure 4 is a block diagram of circuitry for RAM self-repair as described in various representative embodiments consistent with the teachings of the invention.

Figure 5 is another block diagram of circuitry for RAM self-repair as described in various representative embodiments consistent with the teachings of the invention.

Figure 6 is yet another block diagram of circuitry for RAM self-repair as described in various representative embodiments consistent with the teachings of the invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

As shown in the drawings for purposes of illustration, the present patent document relates to novel apparatus for the automatic testing of RAM circuits on-chip.

5 Previous circuitry for on-chip testing have required substantial area on the integrated circuit (IC) chip and have been somewhat removed from the tested area introducing propagation delay errors. By locating the circuitry necessary to perform such test in the addressing and input/output blocks of the RAM, these problems have been reduced.

Also, as shown in the drawings for purposes of illustration, the present patent document relates to novel apparatus for the repair of defective RAM circuits. Previous methods for repair of RAM circuits have typically used techniques such as laser repair which permit the removal of defective parts of the integrated circuit chip and then replacement with a redundant part. However, this process is expensive as an additional processing step is involved. By including the circuitry necessary to repair defects in RAM circuits in the input/output blocks of the RAM, this problem has been negated.

In the following detailed description and in the several figures of the drawings, like elements are identified with like reference numerals.

1. RAM Architecture:

20 Figure 1 is a diagram of the architecture of a RAM circuit 105 as described in various representative embodiments consistent with the teachings of the invention. In figure 1, memory storage cells 110, also referred to herein as storage cells 110 and more concisely as cells 110, are indicated by small squares. For ease of illustration, only one storage cell 110 is labeled in figure 1.

25 A representative example RAM memory, which is not that shown in figure 1, could comprise logically 416 words with 50 bits of data in each word. Using bit-slice architecture for such an example, a slice of cells is created in which each slice represents one bit of data but it is 416 words. During the design phase, a slice is created that is 416 bits high by one bit wide. This slice is then duplicated 50 times to create the complete array. This methodology creates a very tall and fairly narrow array for this example.

30

By designing the RAM array wherein bits occupying an identical ordinal positional in nearby words are moved to adjacent horizontal positions, a better aspect ratio for the array can be obtained. In the example of figure 1, each bit-slice **115** contains eight cells **110** in width instead of one. The array now is only 52 words tall with each word still 50 bits wide. Words now, however, are interleaved on the same row. The aspect ratio of the storage array has become more square in the process resulting in a more compact design. A more compact design is preferable as designs that have long traces running vertically between cells could prevent the RAM from functioning properly at the speeds needed.

The RAM circuit **105** of figure 1 includes a RAM array **250**, also referred to herein as a random access memory array **250**, for storing data. The RAM array **250** is divided into sections referred to herein as slice arrays **118** wherein each slice array **118** includes an associated group of memory storage cells **110**

Also shown in figure 1, each bit-slice **115** includes an I/O circuit **130**, as well as the associated slice array **118**. A control and address block **205** comprises a control circuit **210** and an address selection circuit **120**. The control circuit **210** controls test initiation and progress. The address selection circuit **120** enables the selection of memory storage cells **110** for reading and writing of data. In addition, figure 1 shows error detection circuit **230** which has inputs from the I/O circuits **130** and outputs information regarding any errors found during the test to the control circuit **210**.

2. Overview of Self Test Circuitry:

Figure 2 is a block diagram of an electronic test circuit **200** as described in various representative embodiments consistent with the teachings of the invention. The electronic test circuit **200** is also referred to herein as electronic circuit **200**. The electronic test circuit **200** can be built into the address and I/O circuitry of the RAM circuit **105** and can be programmed to test every cell **110** of the RAM array **250** at wafer test, package test, power-up, as well as other times. The electronic test circuit **200** includes the control circuit **210** which controls the flow of the built-in test and the address selection circuit **120** described above. Data is written into and read out of the bit-slices

115 through the I/O circuit 130 of each bit-slice 115. The results of comparing the data written into the bit-slice 115 and that read out of it is reported to the error detection circuit 230 which reports those results back to the control circuit 210.

Figure 3 is another block diagram of the electronic test circuit 200 as described in various representative embodiments consistent with the teachings of the invention. In figure 3, the various components of the test circuit 200 have been interconnected with other circuits normally present in RAM circuits 105.

3. Detail of Self Test Circuitry - Control Circuit:

10 The control circuit 210 controls the execution of the test that is performed on the RAM array 250. As shown in figure 3, the control circuit 210, has first, second, and third control-circuit inputs 336,337,338 and first, second, third, fourth, and fifth control-circuit outputs 341,342,343,344,345. While shown as a single line, some of these interconnection may, in fact, be multiple wires.

15 There are a variety of industry standard tests some of which are referred to as March tests that can be employed to test the RAM array 250. The March Tests writes preselected patterns in a preselected order into the RAM array 250 and then reads them back out to verify the integrity of the memory storage cells 110. Different March tests perform their tests in a variety of ways such as whether the test sweeps up or down thru the address space of the RAM array 250 and the number of times that the test is repeated. The test or tests performed, however, could be other than a March test. Regardless of the test performed, it is the control circuit 210 that controls the test.

20 As the control circuit 210 interacts with the other elements performing the test, various functions and aspects of the control circuit 210 will be discussed in connection with those other elements.

4. Detail of Self Test Circuitry - Test Address Selection Circuit:

The address selection circuit 120 comprises a sequencer 355, an address multiplexer 365, a RAM address register 305, and a comparator 375.

30 The control circuit 210 sends a first command 350 to the sequencer 355 at a

sequencer control input 356 of the sequencer 355. The sequencer 355 also has sequencer data input 357 and a sequencer output 358. The sequencer 355 increments or decrements a memory address 360, wherein the memory address 360 is the memory address of the cell 110 selected for test and stored in the RAM address register 305. The result of the incrementation/decrementation, i.e., the output value of the sequencer 355, is referred to as an indexed memory address 361. Incrementation and decrementation can occur in random or in a preselected pattern, the simplest being to increment or decrement by a single address space. The sequencer control input 356 receives various commands from the first control-circuit output 341 of the control circuit 210. One of these commands is a command to increment. When the increment command is received, the sequencer 355 increments the memory address 360. Another of these commands is a command to decrement. When the decrement command is received, the sequencer 355 decrements the memory address 360.

The second control-circuit output 342 transmits a second command 363 which is received by the address multiplexer 365 on an address-multiplexer control input 366. The address multiplexer 365 also has first, second and third address-multiplexer data inputs 367, 368, 369 and an address-multiplexer output 370. The first address-multiplexer data input 367 receives the incremented/decremented memory address 360 from the sequencer output 358. The second address-multiplexer data input 368 receives an initial self-test memory address 372, wherein the initial self-test memory address 372 is the memory address 360 of the first cell 110 selected for test. The third address-multiplexer data input 369 receives RAM memory storage cell 110 addresses during normal operation of the RAM circuit 105.

When the second command 363 instructs the address multiplexer 365 to select the first address-multiplexer data input 367 as its active input, the address multiplexer 365 transfers contents of the first address-multiplexer data input 367 to the address-multiplexer output 370. When the second command 363 instructs the address multiplexer 365 to select the second address-multiplexer data input 368 as its active input, the address multiplexer 365 transfers contents of the second address-multiplexer data input 368 to the address-multiplexer output 370. And, when the second command

363 instructs the address multiplexer 365 to select the third address-multiplexer data input 369 as its active input, the address multiplexer 365 transfers contents of the third address-multiplexer data input 369 to the address-multiplexer output 370. The address-multiplexer output 370 transfers its contents to the RAM address register 305.

5 The comparator 375 receives the contents of the RAM address register 305 on a first comparator input 376. The comparator 375 also has a first comparator output 377 and a second comparator output 378. The comparator 375 compares the contents of the RAM address register 305 to the initial self-test memory address 372 and to a final self-test memory address 379. Final self-test memory address 379 is not shown on any of the
10 drawings. For comparison purposes, both the initial self-test memory address 372 and the final self-test memory address 379 could be, for example, hard wired into the comparator 375, obtained from the control circuit 210, or obtained by other means. When the contents of the RAM address register 305 is the same as the initial self-test memory address 372, the first comparator output 377 is set to indicate that the contents
15 of the RAM address register 305 is the same as the initial self-test memory address 372, i.e., at the beginning of the test. When the contents of the RAM address register 305 is the same as the final self-test memory address 379, the second comparator output 378 is set to indicate that the contents of the RAM address register 305 is the same as the final self-test memory address 379, i.e., the end of test has been reached.

20 The first control-circuit input 336 receives the contents of the first comparator output 377. When the first comparator output 377 indicates that the contents of the RAM address register 305 is the same as the initial self-test memory address 372, the control circuit 210 is so informed at first control-circuit input 336. When the second comparator output 378 indicates that the contents of the RAM address register 305 is the same as the
25 final self-test memory address 379, the control circuit 210 is so informed at second control-circuit input 337. The control circuit 210 may sweep through various test sequences and may repeat those test sequences in various orders before it terminates the test.

30 An important characteristic of the control circuit 210 is that it is independent of the size of the RAM. It has no knowledge or dependence on the size of RAM addressing.

It uses the initial self-test memory address **372** comparison result as reported at the first comparator output **377** and the final self-test memory address **379** comparison result as reported at the second comparator output **378** to tell it where to start and where to stop testing. As a result, once designed the control circuit **210** can be used again and again for
5 different RAM blocks on different integrated circuit chips.

5. Detail of Self Test Circuitry - I/O circuit:

Again in figure 3, various components of the test circuit **200** have been interconnected with other circuits normally present in RAM circuits **105**. During normal
10 operation, operational data **380** is inputted into input register **381** and is written into the slice array **118**. Data is retrieved from the slice array **118** and written into output register **383**.

The I/O circuit **130** comprises components common to the bit-slice **115**, the input register **381** and the output register **383**, as well as a data-in multiplexer **1305**, an inverter
15 **1315**, an input-complement multiplexer **1320**, an output-complement multiplexer **1330**, and an exclusive-OR gate **1340**. All components are present in the I/O circuit **130** regardless of whether tests are being performed or normal data operations are progressing. The data is merely routed according to the operating mode. An input path from the input-complement multiplexer **1320** to the slice array **118** and an output path
20 from the slice array **118** to the output register **383** are shown in figure 3. However, in other embodiments both paths could time share the same transmission path.

The data-in multiplexer **1305** has first and second data-in-multiplexer data inputs **1306,1307**, a data-in-multiplexer control input **1308**, and a data-in-multiplexer output **1309**. The first data-in-multiplexer data input **1306** receives a test data **1310**, and the
25 second data-in-multiplexer data input **1307** receives operational data **380**.

When the control circuit **210** instructs the data-in multiplexer **1305** that it is executing the test, the third control-circuit output **343** transmits a command to the data-in-multiplexer control input **1308** to select the first data-in-multiplexer data input **1306** as the active input and to transfer contents of the first data-in-multiplexer data input **1306**
30 to the data-in-multiplexer output **1309**. Otherwise, the third control-circuit output **343**

transmits a command to the data-in-multiplexer control input **1308** to select the second data-in-multiplexer data input **1307** as the active input and to transfer contents of the second data-in-multiplexer data input **1307**, i.e., normal operational data **380**, to the data-in-multiplexer output **1309**. The data-in-multiplexer control input **1308** is preferably two
5 bits wide to accommodate the required commands.

The input register **381** receives data from the data-in-multiplexer output **1309**, and the inverter **1315** receives data from the input register **381**.

The input-complement multiplexer **1320** has first and second input-complement-multiplexer data inputs **1321,1322**, an input-complement-multiplexer control input **1323**,
10 and an input-complement-multiplexer output **1324**. The first input-complement-multiplexer data input **1321** receives data from the input register **381**, and the second input-complement-multiplexer data input **1322** receives the output of the inverter **1315**.

The output-complement multiplexer **1330** has first and second output-complement-multiplexer data inputs **1331,1332**, an output-complement-multiplexer control input **1333**, and an output-complement-multiplexer output **1334**. The first output-complement-multiplexer data input **1331** receives data from the input register **381**, and the second output-complement-multiplexer data input **1332** receives the output of the
15 inverter **1315**.

When the control circuit **210** instructs the input-complement multiplexer **1320**
20 that it is to write the test data **1310**, the fourth control-circuit output **344** transmits a command to the input-complement-multiplexer control input **1323** to select the first input-complement-multiplexer data input **1321** as the active input and to transfer contents of the first input-complement-multiplexer data input **1321** to the input-complement-multiplexer output **1324**. When the control circuit **210** instructs the input-complement
25 multiplexer **1320** that it is to write the inverse test data, the fourth control-circuit output **344** transmits a command to the input-complement-multiplexer control input **1323** to select the second input-complement-multiplexer data input **1322** as the active input and to transfer contents of the second input-complement-multiplexer data input **1322** to the input-complement-multiplexer output **1324**.

30 During normal operation, i.e., not test, the input-complement multiplexer **1320**

transfers operational data 380 stored in the input register 381 from first input-complement-multiplexer data input 1321 to the input-complement-multiplexer output 1324.

5 The output-complement multiplexer 1330 and the exclusive-OR gate 1340 are used to compare the data read from the slice array 118 with the expected value as stored in the input register 381.

10 The output-complement multiplexer 1330 has first and second output-complement-multiplexer data inputs 1331,1332, the output-complement-multiplexer control input 1333, and the output-complement-multiplexer output 1334. The first output-complement-multiplexer data input 1331 receives data from the input register 381, and the second output-complement-multiplexer data input 1332 receives the output of the inverter 1315.

15 When the control circuit 210 instructs the output-complement multiplexer 1330 that it is to select the test data for comparison which is stored in the input register 381, the fifth control-circuit output 345 transmits command to the output-complement-multiplexer control input 1333 to select the first output-complement-multiplexer data input 1331 as the active input and to transfer contents of the input register 381 to the output-complement-multiplexer output 1334, otherwise the fifth control-circuit output 345 transmits command to the output-complement-multiplexer control input 1333 to
20 select the second output-complement-multiplexer data input 1332 as the active input and to transfer contents of the inverter output 1315 to the output-complement-multiplexer output 1334. During normal operation, it is irrelevant whether first output-complement-multiplexer data input 1331 or second output-complement-multiplexer data input 1332 is transferred to the output-complement-multiplexer output 1334. However, in the
25 representative embodiment, the first output-complement-multiplexer data input 1331 is transferred to the output-complement-multiplexer output 1334.

30 The exclusive-OR gate 1340 has first and second exclusive-OR-gate inputs 1341,1342 and an exclusive-OR-gate output 1343. The first exclusive-OR-gate input 1341 receives data from the output register 383, and the second exclusive-OR-gate input 1342 receives the output-complement-multiplexer output 1334.

The exclusive-OR gate 1340 is used to compare the data read from the slice array 118, which is stored in the output register 383 and presented to the first exclusive-OR-gate input 1341 with the expected value which is stored in the input register 381 and presented to the second exclusive-OR-gate input 1342. When the data in the output register 383 matches that of the expected data the exclusive-OR gate 1340 outputs a binary zero to the exclusive-OR-gate output 1343 indicating a success. Otherwise, the exclusive-OR gate 1340 outputs a binary one to the exclusive-OR-gate output 1343 indicating a failure.

6. Detail of Self Test Circuitry - Error detection circuit:

The error detection circuit 230 has a plurality of error detection circuit inputs 231 and a single error detection circuit output 232. The output of each exclusive-OR-gate output 1343 is transferred to its associated error detection circuit input 231. The error detection circuit 230 combines the results of the exclusive-OR gates 1340 for every bit-slice 115 and reports the result to the control circuit 210 via the error detection circuit output 232 to the third control-circuit input 338.

7. Redundant RAM Model:

Figure 4 is a block diagram of circuitry for RAM self-repair as described in various representative embodiments consistent with the teachings of the invention. In figure 4, the RAM array 250 is divided into bit-slices 115, each of which includes its associated slice array 118 and I/O circuit 130 as previously stated. The RAM array 250 also comprises a redundant slice 410. Should the RAM array 250 not have any defects, the redundant slice 410 is not used. However, should a defect be encountered, data flow is routed around the bit-slice 115 containing the defect, and the redundant slice 410 is used in its place. The following error types, which are the five most common defect mechanisms, can be corrected using the techniques disclosed herein: (1) single bit, (2) paired bit (two adjacent bits within the same slice), (3) single column, and (4) paired column (two adjacent columns within the same slice), and (5) slice. Essentially any and all defects occurring in the same slice can be repaired as repair occurs via a remapping

of slices.

In the example of figure 4, the bit-slice 115 corresponding to k-th bit-slice 115 contains a defect 415 which is corrected by rerouting bit-slice I/O for all bit-slices 115 to the right of and including the bit-slice 115 for the k-th bit-slice 115. Each bit-slice
5 comprises two I/O paths, a normal bit-slice I/O path 420 and a alternate bit-slice I/O path 425. Bit-slices 115 to the left of the bit-slice 115 containing the defect 415 utilize their normal bit-slice I/O paths 420 for input/output of those bit-slices 115. The bit-slice 115 containing the defect 415 and all bit-slices 115 to the right of that bit-slice 115 utilize their alternate bit-slice I/O paths 425 for input/output of those bit-slices 115. Thus, all
10 bit-slices 115 to the right of the bit-slice 115 containing the defect 415, as well as the redundant slice 410, are mapped to the I/O circuit 130 to their immediate left.

8. Overview of Redundant RAM Circuitry:

Figure 5 is another block diagram of circuitry for RAM self-repair as described in various representative embodiments consistent with the teachings of the invention. As in figure 4, it is assumed that a defect occurs in the k-th slice array 118. In such case, a remap register 515 for the k-th bit-slice 115 informs remap selector circuit 520 to redirect data for the k-th bit-slice 115 to the (k-1)-th bit-slice 115 for storage in the (k-1)-th slice array 118. The remap selector circuit 520 in turn instructs a write selector circuit 505 for the k-th bit-slice 115 to write the data for the k-th bit-slice 115 into the (k-1)-th slice array 118.
15

The remap register 515 for the k-th bit-slice 115 informs remap selector circuit 520 to redirect data read from the (k-1)-th slice array 118 to the k-th bit-slice 115 for transfer out. The remap selector circuit 520 in turn instructs a read selector circuit 510 for the k-th bit-slice 115 to read the data for the k-th bit-slice 115 from the (k-1)-th slice array 118.
20 25

Figure 6 is yet another block diagram of circuitry for RAM self-repair as described in various representative embodiments consistent with the teachings of the invention. Figure 6 shows various circuitry from previous figures. In particular this
30 circuitry includes (1) the input register 381, (2) the input-complement multiplexer 1320,

(3) the output-complement multiplexer 1330, (4) the slice array 118, (5) the output register 383, and (6) the exclusive-OR gate 1340.

In addition to the circuitry used for normal RAM read/write functions and defect detection, circuitry necessary for defect repair is as follows: (1) a write multiplexer 605,
5 (2) a read multiplexer 610, (3) the remap register 515, and (4) an OR gate 620. The write multiplexer 605 has first and second write-multiplexer inputs 606,607, a write-multiplexer control input 608, and a write-multiplexer output 609. The read multiplexer 610 has first and second read-multiplexer inputs 611,612, a read-multiplexer control input 613, and a read-multiplexer output 614. The remap register 515 has a remap-
10 register input 616 and a remap-register output 617. The OR gate 620 has first and second OR-gate inputs 621,622 and an OR-gate output 623.

As long as no defects 415 occur to the left of or in bit-slice "k" 115 in figure 6, the write multiplexer 605 is enabled so as to write operational data 380 from the input register 381 into its associated bit-slice 115 through input-complement multiplexer 1320.
15 The function of input-complement multiplexer 1320 was explained in the discussion of figure 3. Also, the read multiplexer 610 is enabled so as to read data stored in the associate RAM bit-slice 115 into the output register 383 associated with that RAM bit-slice 115. When the output of the OR gate 620, identified as OR-gate output 623, is a binary zero, both inputs to the OR gate 620, identified as first OR-gate input 621 and
20 second OR-gate input 622, are binary zero. The binary zero at the first OR-gate input 621 indicates that no defects were found in any of the bit-slices 115 to the left of the k-th bit-slice 115, and the binary zero at the second OR-gate input 622 indicates that the k-th bit-slice 115 is free of defects 415. The fact that no defects 415 were found in the k-th bit-slice 115 during the test phase is recorded in the remap register 515 by storing a binary
25 zero in it.

If, however, a defect 415 occurs in the k-th bit-slice 115 that fact is recorded in remap register 515. The fact that defect 415 is present in the k-th bit-slice 115 would have been detected during the test phase. In a representative application, the remap register 515 then would have a binary one value stored in it. The OR-gate output 623
30 then becomes a binary one which switches the k-th write multiplexer 605 to write the

value from the (k+1)-th input register 381 into the memory of the k-th bit-slice 115. This action is, however, of no consequence as any data in the k-th bit-slice 115 will be ignored since it is known to have the defect 415. Of more importance is the fact that the read multiplexer control input switches the read multiplexer 610 for the k-th bit-slice 115 to read data from the (k-1)-th bit-slice 115 into the output register 383 for the k-th bit-slice 115 instead of the (k-1)-th bit-slice 115.

Since the OR-gate output 623 for the k-th bit-slice 115 provides the first OR-gate input 621, the OR-gate output 623 for the (k-1)th bit-slice 115 becomes a binary one indicating that the defect 415 occurred in a bit-slice 115 prior to that of the (k-1)th bit-slice 115. This value for the output of the OR gate 620 for the (k-1)th bit-slice 115 switches the write multiplexer 505 for the (k-1)-th bit-slice 115 to write the operational data 380 from the input register 381 of the k-th bit-slice 115 to be written into the memory of the (k-1)-th bit-slice 115.

In a manner similar to that described above, the data stored in the (k-2)th bit-slice 115 will be read out by the read multiplexer 610 of the (k-1)-th bit-slice 115 into the output register 383 of the (k-1)-th bit-slice 115. Thus, all remapping of data for both read and write functions is programmed into the remap registers 515 when the RAM array 250 is tested.

9. Concluding Remarks:

In representative embodiments of the apparatus described in the present patent document, techniques for the on-chip testing of RAM circuits on-chip are disclosed. Present techniques for on-chip testing do not require substantial area on the chip and are inherently located closer to the tested area which reduces propagation delay errors. By locating the circuitry necessary to perform such test in the addressing and input/output blocks of the RAM, these advantages have been obtained.

In other representative embodiments of the apparatus described in the present patent document, techniques for the soft repair of defective RAM circuits are disclosed. Present techniques for repair of RAM circuits do not use techniques such as laser repair in the removal of defective parts of the IC and its replacement with a redundant part. The

present process is inexpensive and no additional processing steps are involved. By including the circuitry necessary to repair defects in RAM circuits in the input/output blocks of the RAM, these advantages have been obtained.

5 While the present invention has been described in detail in relation to representative embodiments thereof, the described embodiments have been presented by way of example and not by way of limitation. It will be understood by those skilled in the art that various changes may be made in the form and details of the described embodiments resulting in equivalent embodiments that remain within the scope of the appended claims.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2